

# 900 MHz Audio / Video Splitters



TECHNICAL SHEETS ARE SUBJECT TO CHANGE WITHOUT NOTICE.

### **Applications**

Vericom 900 MHz Audio / Video Splitters distribute your HDTV, CATV, off-air, analog or digital RF signal and are intended for indoor use only.

#### **Description / Specifications**

This splitter is manufactured with a durable die-cast zinc housing, and a built-in ground terminal for frequencies up to 900 MHz.

#### **Features & Benefits**

- · Low cost 900 MHz splitter with high isolation
- · Distributes your RF signal to multiple locations
- · Nickel plated connectors for corrosion resistance
- · Durable die-cast zinc housing
- 2-Way, 3-Way, 4-Way, and 6-Way models available
- Indoor use only
- No PCB board
- · Mounting screws provided

#### Electrical

Model	IL (dB)	Input RL (dB)	Isolation Between Outputs (dB)	
	5-900 MHZ	5-900 MHZ	5-47 MHZ	47-900 MHZ
2-Way	5.0	11.0	9.5	15.0
3-Way	4.5 (1 Port) 10.0 (2 Ports)	10.1	9.0	10.0
4-Way	9.5	9.3	11.0	13.0
6-Way	10.5 <i>(4 Ports)</i> 15.0 <i>(2 Ports)</i>	7.5	10.0	10.0

## **Ordering Information**

Description				
900 MHz Audio / Video Splitter				
Item No.	Model			
WRF29-03563	2-Way			
WRF39-03564	3-Way			
WRF49-03565	4-Way			
WRF69-03566	6-Way			

REV.20210202.2

## © 2021 Vericom Global Solutions info@vericomsolutions.com • vericomsolutions.com